

Expansion module for L-CON-LOG series. 4 x Analog inputs, 2 x Analog Output, Digital input 4 x, 4 x Digital output

FEATURES

- Multifunction concealed board with 4 x AI, AO x 2, 4 x DI, 4 XDO individual channel configuration
- Jumper selectable voltage- or current input
- Broken kabeldetektion by current measurement
- Configurable settings for the initial value
- digital input channels can be used as 32-bit counters
- 120 VDC surge protection to the analog input
- 60 VDC surge protection for digital input
- Overload protection for digital output
- Short circuit protection for digital output



SPECIFICATIONS

Indgang	:	4 stk. ± 1 V, ± 2.5 V, ± 5 V, ± 10 V, ± 20 mA, 0 ~ 20 mA, 4 ~ 20 mA (Jumper Selectable)
Indgang	:	4 stk. kontakt (slutte)
Udgange	:	2 stk. 0 V ~ +5 V, ± 5 V, 0 V ~ +10 V, ± 10 V, 0 mA ~ +20 mA, +4 mA ~ +20 mA (Jumper Selectable)
Udgange	:	4 stk. 650mA maks. 10 til 40 volt Open collector

