

IPP17N4200

17" Panel PC med PCAP touch, Intel Pentium N4200
Quad Core op til 2.5GHz CPU panel montage IP65
front, 9~48VDC

FEATURES

- 17" TFT SXGA 5:4 LCD capacitive Touch
- Pentium N4200
- 1x DDR3L SO-DIMM MAX. 8GB RAM (leveres uden, få pris med ram)
- Opløsning Op til 1280 x 1024 (SXGA)
- 350 nits Lysstyrke
- Designet med Aluminium
- IP65 Kompatibel frontpanel
- 1xVGA, 1xDP (triple display)
- 1x 2.5" SATA Drive (leveres uden, få pris med SSD monteret)
- 1x MSATA
- 2x LAN RJ45 Intel I210 (POE OPTION ADD ON)
- 4x USB 3.0
- 4x RS232/422/485
- 8x Isoleret DIO
- 2x Mini-PCI
- SIM Sokkel
- SUPPORT OS: WINDOWS 10/11
- 9~48VDC via 3-pin Terminal Block



SPECIFICATIONS

CPU	:	Intel® Pentium® N4200
Storage	:	SATA2 1x 2.5" SATA2.0 HDD / SSD Slot
USB	:	4x USB 3.0 (Type-A)
Driftstemperatur	:	0°C ~ 50°C / 32°F ~ 122°F (Standard)
Driftstemperatur	:	-20 to 70C
BIOS	:	AMI uEFI BIOS w/ 64Mb SPI Flash
Antenne	:	4x Antenne holes
Approval	:	CE, FCC Class A
Betjening	:	1x Power LED (on front), 1x Power Switch (on rear)
Chok/Vibration	:	Operating, 1.5 Grms, 5-500 Hz, 3 Axes (w/ SSD, according to IEC60068-2-64)
Ethernet	:	10/100/1000 LAN 2 (RJ-45 on rear, 1x Intel® I210-AT, 1x Realtek RTL8111G)
Forsyning	:	9~48VDC via 3-pin Terminal Block



SPECIFICATIONS

Hukommelse	:	1x DDR3L 1333 SO-DIMM up to 8GB
Hukommelse	:	1x DDR3L 1333/1600/1866 MHz 204-Pin SO-DIMM Socket (8GB max)
IP-Tæthed	:	IP65 (Front)
Luftfugtighed	:	0% ~ 95%
Lyd	:	Realtek ALC888-GR
Montering	:	Panel Mount, VESA Mount
mPCIe	:	2x Full-size Mini-PCIe Sockets
Msata	:	1 (full size)
OS SUPPORT	:	WIN10
PoE	:	NEED opgrade modul. Not included
Porte	:	4x RS-232/422/485 with Auto Flow Control Support 5V/12V, DB9



**DANBIT**

IPP17N4200

SPECIFICATIONS

SSD	:	1x 2.5" HDD/SSD Drive Bay (SATA 3.0)
Udgange	:	1x CDS, 1x VGA, 1x DisplayPort
Dimensioner	:	442 x 354 x 58 mm / 17.40" x 13.94" x 2.28" (W x H x D)



Danbit A/S Værkstedvej 39 Køge, 4600 Denmark



+45 56662020



salg@danbit.dk

For business customers only (B2B). Prices exclude VAT. We reserve the right to correct errors and make changes.