

USB-COUNT

8 channel frequency counter, max. 500kHz via USB.
Pulse count up/down or phase A/B. Powered from USB
port

FEATURES

- Versatile frequency counter, pulse counter via the USB port
- Powered from the USB port
- A total of 8 entries, of which:
 - 4 channels for UP/DOWN, DIR/PULSE, Phase AB
 - 8 channels for Count-Up and frequency counter
- 32 bit resolution
- Max. 500kHz (non-isolated)
- Input voltage: 0 - +30V
- USB 2.0
- YOUR assembly
- Dimensions: 107 x 102 x 33 mm
- Operating temperature: -25 - + 75°C



SPECIFICATIONS

Forsyning	:	Via USB porten
Indgang	:	Ikke isoleret Logisk 0: 0 - 0,8 V, Logisk 1: 2 - 5 V. Isoleret Logisk 0: 0 - 1 V Logisk 1: 4,5 - 30 V
Isolation	:	2500 VDC
Montering	:	DIN-skinne
Software	:	USB driver til Windows 2000,XP, Win7 og Win8
Stik	:	USB type B og skrueterminaler
Dimensioner	:	102 x 33 x 107 mm

