# XVA-44, 4 x 4 VGA Matrix med lyd

## FEATURES

Route 2/4 different VGA and audio sources to 4 different displays and speakers

Support 1. Button front panel control 2. IR remote control

Remotely control up to 5 meters by using the remote controller

Switch both video and audio directly

Turn ON/OFF each video / audio output port individually

Activate Auto Scan by front push buttons

Selectable Scan Time interval

remote controller with embedded functions to control up to 16 units

Each input can be independently connected to any one or all outputs

Support video bandwidth up to 300 MHz

Support the video resolution of 1920 x 1440

System settings are automatically retained, and reset to the previous settings after a power failure

Rack mountable



---

Danbit A/S Værkstedsvej 39 Køge, 4600 Denmark     +45 56662020     salg@danbit.dk