

Udendørs trådløs PIR sensor - infrarød bevægelsessensor med antenne, batteridrevet, 35 m FEATURES

- Trådløs infrarød udendørs PIR bevægelsessensor
- Ekstern antenne
- Justerbar rækkevidde sensor 10-35m/750 kvm
- Batteridrevet 2 x AAA 1,5 volt
- Driftstemperatur -20 til +55°
- IP55 tæt
- 150 meter line-of-sight
- Til vægmontering (beslag medfølger)
- Systemet virker ikke uden receiver PIR-WL-R



SPECIFICATIONS

Driftstemperatur	:	-20° C + 55° C
Andet	:	Digital integral white light filter. 16 million possible identification codes Adjustments Detection signal (CCTV) timer 0.4 to 60 secs. Light level signal 2 Lux to daylight. Pulse count 1 (2 & 3 - 6 seconds)
Batteri	:	2 x AAA (not included)
Batteri	:	Ca. 2 år
IP-Tæthed	:	Detector Housing ABS high impact IP55 rated
Montering	:	3m high for multibeam coverage, 6m high for curtain coverage and 1.5m with mask for pet immunity
Rækkevidde	:	Transmission 150 metres line-of-sight: 433.92 MHz frequency - SAW stabilised
Sensor	:	Coverage Range 10 to 35 metres: 35 x 30 m with 90° multi function lens
Vægt	:	152g
Dimensioner	:	110 x 100 x 100mm (HxWxD)

