

## KAM-U-BULL-ALARM

3MP udendørs bullet kamera med alarmgenerering  
ved ændring i valgt areal, 1920x1080, Android/iOS  
APP

## FEATURES

- 3 Mega pixel Bulletkamera med alarmeringskontrol.
- Vælg eget areal på kameraet for alarmering
- 1/2.8" Cmos Sensor
- Supporterer ONVIF
- Smartphone videoovervågning (Android, iOS)
- Web, CMS og mobile applikation



## SPECIFICATIONS

|                  |   |                                                                                                      |
|------------------|---|------------------------------------------------------------------------------------------------------|
| Video            | : | H.265/H.265X/H.265 AI, Main Stream 2Mbps~8Mbps, Sub Stream 512kbps~2.5Mbps (adjustable), JPEG format |
| Driftstemperatur | : | -30°C ~ 60°C                                                                                         |
| Afstand          | : | IR afstand, 35m                                                                                      |
| Alarm            | : | Motion Detect, Video Loss, Video Cover, Network Abnormal                                             |
| Ethernet         | : | Adaptive 10/100M RJ45                                                                                |
| Interface        | : | SD slot, RJ485                                                                                       |
| IP-Tæthed        | : | IP67                                                                                                 |
| LED              | : | 6pcs Array LEDs, 35m Night Vision, 0.001Lux @ (F1.2, AGC ON), 0 Lux with IR                          |
| Linse            | : | 3.6mm or 6mm 3mp Fixed Lens                                                                          |
| Opløsning        | : | 3MP, 1920x1080                                                                                       |
| PoE              | : | Built-in POE, IEEE802.3af)                                                                           |
| Sensor           | : | 1/2.8" Sony IMX323 Cmos Sensor                                                                       |



**DANBIT**

KAM-U-BULL-ALARM

## SPECIFICATIONS



Danbit A/S Værkstedvej 39 Køge, 4600 Denmark



+45 56662020



salg@danbit.dk

For business customers only (B2B). Prices exclude VAT. We reserve the right to correct errors and make changes.