

X-KEYS - Programmable USB switch box to 6 / 12
(dual cable) external contacts. USB HID commands.
acquisition contacts

FEATURES

- USB Switch interface
- 6 input ports for push buttons with 3.5mm jack connector.
- 3.5mm Jack is stereo and can handle 2 push buttons
- if 12 push buttons, then with optional splitter cable
- For USB Port
- Mounting Flanges
- Any button pressure can trigger USB HID command
- Software for button macro programming
- setup lies in the device



SPECIFICATIONS

Operating Temp.	:	-20 to 60 C
Farve	:	Black
Andet	:	HID keyboard, HID mouse, HID game controller, HID multimedia
Forsyning	:	Power Source USB port, nominal voltage - 5 VDC Power Consumption 21 mA @ 5 VDC
Features	:	Programmable
IP-Tæthed	:	IP 40, typical indoor office environment
OS SUPPORT	:	Use: Any OS via USB HID Programming: Windows XP through 10, Mac OS X 10.4 through 10.10
Porte	:	6 ports (split to 12 with optional Y cords)
Software	:	Windows: MacroWorks 3.1 Android: X-keys Android Mac OS X: ControllerMate
Stik	:	Wired USB 2.0 standard "A" plug
Tilslutning	:	USB
Weight	:	160 g



**DANBIT**

USB-KEY6SW

SPECIFICATIONS



Danbit A/S Værkstedvej 39 Køge, 4600 Denmark



+45 56662020



salg@danbit.dk

For business customers only (B2B). Prices exclude VAT. We reserve the right to correct errors and make changes.